

Coilcraft S-Parameter Data for RF Surface Mount Inductors 0603CS Series Chip Inductors

Coilcraft, Inc.
Version 0603CS April, 2004


Coilcraft two-port S-parameter data files are based on empirical measurements of Coilcraft RF Surface Mount Inductors. The data files are used as "black box" descriptions, thus reducing complexity in circuit modeling. For one-port applications, simply connect one terminal of the component to ground in your circuit simulator software.

The data files represent de-embedded measurements. Effects due to customer circuit board traces, board materials, ground planes, or interactions with other components are not included and can have a significant effect when comparing the S-parameters to measurements of the inductors using typical production verification instruments and fixtures.

Typically, the Self Resonant Frequency (SRF) of the component model will be higher than the measurement of the component mounted on a circuit board. The parasitic reactive elements of a circuit board or fixture will effectively lower the circuit resonant frequency, especially for very small inductance values. Since data sheet specifications are based on typical production measurements, and the S-parameter models are based on de-embedded measurements as described below, the S-parameter model results may be different from the data sheet specifications.

S-parameter modeling method

The measurements for this series were made over a brass ground plane, with each component centered over a 0.026 inch wide air gap, as illustrated below. The test pads were (50 Ohm) 30 mil wide traces of tinned gold over 25 mil thick alumina, and were not included in the gap. The TRL* calibration plane is also illustrated below.



The S-parameters were generated by matching a simulation model as closely as possible to an average of the original measurements. The model was then used to create the final S-parameters. This method results in a model that represents as closely as possible the typical frequency-dependent behavior of the component up to a frequency just above the self-resonant frequency of the model. The valid frequency range for each part is specified in Table 1 below.

**Coilcraft S-Parameter Data for RF Surface Mount Inductors
0603CS Series Chip Inductors**

Table 1
Valid Frequency Range of S-parameters

Part Number	Range (MHz)		Part Number	Range (MHz)		Part Number	Range (MHz)
0603CS-1N6	1 - 25300		0603CS-11N	1 - 7800		0603CS-56N	1 - 3200
0603CS-1N8	1 - 22100		0603CS-12N	1 - 6700		0603CS-68N	1 - 2800
0603CS-2N2	1 - 23000		0603CS-15N	1 - 6500		0603CS-72N	1 - 3100
0603CS-3N3	1 - 17100		0603CS-16N	1 - 6200		0603CS-82N	1 - 2900
0603CS-3N6	1 - 14600		0603CS-18N	1 - 5400		0603CS-R10	1 - 2500
0603CS-3N9	1 - 13700		0603CS-22N	1 - 5600		0603CS-R11	1 - 2400
0603CS-4N3	1 - 12900		0603CS-23N	1 - 5500		0603CS-R12	1 - 2300
0603CS-4N7	1 - 12500		0603CS-24N	1 - 4800		0603CS-R15	1 - 2000
0603CS-5N1	1 - 10700		0603CS-27N	1 - 5300		0603CS-R18	1 - 1900
0603CS-5N6	1 - 10600		0603CS-30N	1 - 4500		0603CS-R20	1 - 2000
0603CS-6N8	1 - 10500		0603CS-33N	1 - 3700		0603CS-R21	1 - 2000
0603CS-7N5	1 - 9600		0603CS-36N	1 - 4200		0603CS-R22	1 - 1700
0603CS-8N2	1 - 8100		0603CS-39N	1 - 3800		0603CS-R25	1 - 1700
0603CS-8N7	1 - 7200		0603CS-43N	1 - 4000		0603CS-R27	1 - 1600
0603CS-9N5	1 - 9300		0603CS-47N	1 - 3400		0603CS-R33	1 - 1400
0603CS-10N	1 - 8500		0603CS-51N	1 - 3800		0603CS-R39	1 - 1300

How to use the files

The chip inductor data file names have the format XXWWZZZ.S2P:

- XX = the first two digits of the inductor part number
- WW = the specific inductor series (CS, HS, PS, CT, HT, LS)
- ZZZ= the nominal inductance value stated on the data sheet

For example, if you were interested in a Coilcraft 0603CS chip inductor with an inductance of 5.1 nH, the file you would choose is 06CS5N1.S2P

S-parameter file description.

All of the S-parameter data files are in the TouchStone format. The following is a typical data segment of a two-port file:

```
# MHZ S MA R 50
!Freq MagS11 AngS11 MagS21 AngS21 MagS12 AngS12 MagS22 AngS22
1 0.001 59.879 1.000 -0.036 1.000 -0.036 0.001 59.879
22.19 0.014 83.698 0.999 -0.798 0.999 -0.798 0.014 83.698
43.38 0.027 84.582 0.998 -1.558 0.998 -1.558 0.027 84.582
....
```

Coilcraft S-Parameter Data for RF Surface Mount Inductors 0603CS Series Chip Inductors

The first line (header) describes the frequency units, parameter, measurement format and characteristic impedance of the measurement (50 Ohms).

The first column is the frequency in MHz. The next columns are the S-parameters as described in the column headings.

Disclaimer

Coilcraft makes every attempt to provide accurate measurement data and software, representative of our components, in a usable format. Coilcraft, however, disclaims all warrants relating to the use of its data and software, whether expressed or implied, including without limitation any implied warranties of merchantability or fitness for a particular purpose. Coilcraft cannot and will not be liable for any special, incidental, consequential, indirect or similar damages occurring with the use of the data and/or software.